

## Bill of Materials

VIN = 12V, VOUT = 5.0V, IOUT = 2A, fsw = 650kHz						
Reference	Count	Part Number	Value	Description	Package	Manufacturer
U1	1	RT6252BHGGJ6F	RT6252BHGGJ6F	Step-Down Converter	TSOT 23-6	RICHTEK
C1,C2	2	GRM219R60J226ME47D	22μF	Capacitor, Ceramic, 6.3V, X5R	0805	MURATA
C4, C5	2	GRM21BR61E106KA73L	10μF	Capacitor, Ceramic, 25V, X5R	0805	MURATA
C6, CBOOT	2	0603B104K500CT	0.1μF	Capacitor, Ceramic, 50V, X7R	0603	WALSIN
CFF	1	0603N220J500LT	47pF	Capacitor, Ceramic, 50V, NPO	0603	WALSIN
R1	1	WR06X1003FTL	100k	Resistor, Chip, 1/10W, 1%	0603	WALSIN
R2, RBOOT, RT	3	WR06X000 PTL	0k	Resistor, Chip, 1/10W, 1%	0603	WALSIN
RFB1	1	WR06X5492FTL	54.9k	Resistor, Chip, 1/10W, 1%	0603	WALSIN
RFB2	1	WR06X1002FTL	10k	Resistor, Chip, 1/10W, 1%	0603	WALSIN
L1	1	LSXNH8080YBL4R7NJG	4.7μH	Inductor	L-8x8	TAIYO YUDEN

## More Information

For more information, please find the related datasheet or application notes from Richtek website <http://www.richtek.com>.

## Important Notice for Richtek Evaluation Board

THIS DOCUMENT IS FOR REFERENCE ONLY, NOTHING CONTAINED IN THIS DOCUMENT SHALL BE CONSTRUED AS RICHTEK'S WARRANTY, EXPRESS OR IMPLIED, UNDER CONTRACT, TORT OR STATUTORY, WITH RESPECT TO THE PRESENTATION HEREIN. IN NO EVENT SHALL RICHTEK BE LIABLE TO BUYER OR USER FOR ANY AND ALL DAMAGES INCLUDING WITHOUT LIMITATION TO DIRECT, INDIRECT, SPECIAL, PUNITIVE OR CONSEQUENTIAL DAMAGES.